

ORTHOGONAL MODE TRANSDUCER

6L

FREQUENCY RANGE [MHz]	R.L. [dB]	Insertion Loss [dB]	Isolation [dB]	XPD [dB]	Interface
5900-6400	> 18	≤ 0,5 dB	> 35	> 30	WR137

6U

FREQUENCY RANGE [MHz]	R.L. [dB]	Insertion Loss [dB]	Isolation [dB]	XPD [dB]	Interface
6400-7100	> 18	≤ 0,5 dB	> 35	> 30	WR137

7 GHz

FREQUENCY RANGE [MHz]	R.L. [dB]	Insertion Loss [dB]	Isolation [dB]	XPD [dB]	Interface
7100-7700	> 18	≤ 0,5 dB	> 35	> 30	WR112

8 GHz

FREQUENCY RANGE [MHz]	R.L. [dB]	Insertion Loss [dB]	Isolation [dB]	XPD [dB]	Interface
7700-8500	> 18	≤ 0,5 dB	> 35	> 30	WR112